

In-Line Fuseholders for 1/4" x 1-1/4" Fuses



Description

The 150312 & 150322 are 500 VAC/VDC rated inline fuseholder ideal for applications where supplemental protection is needed, such as lighting ballasts and power supplies. 8-inch pre-stripped wire leads and fuse clips come pre-assembled for quick installation.

Features/Benefits

- High voltage rating accommodates many power applications
- Wire leads are pre-attached to fuse clips for quick assembly
- Single piece molded body
- UL Recognized to UL/CSA 4248.1

Agency Approval

Agency	Agency File Number
c UL us	E14721

Additional Information



Datasheet



Resources




Samples

Specifications

Voltage Rating	500 VAC/VDC
Ampere Rating	15 A
Fuse Type	1/4" x 1-1/4"
Fuse Clips	Tin-plated brass
Wire	Black 18 AWG for 150322 and Blue 16 AWG for 150312. Both 150° C Stranded
Molded Body	Single piece thermoplastic
Flammability Rating	UL94 V-0
Environmental	RoHS compliant and Pb free
Storage Temperature	-40° C to 80° C
Operating Temperature	-55° C to 85° C

Note: Refer to Fuseology for information on proper fuseholder re-rating.

Dimensions in mm (inches)



Ordering Information

Catalog Number	System Number	Standard Pack	Wire Spec	Wire Color
150312	01500312H	100 Pieces	16 AWG Tin Plated Copper, UL 1230 (105C°)	Blue
150322	01500322H	100 Pieces	18 AWG Tin Plated Copper, UL 3321 (150C°)	Black
150322	01500322HXBLK	100 Pieces	18 AWG Bare Copper, UL 3321 (150C°)	Black
150322	01500322HXGRE	100 Pieces	18 AWG Bare Copper, UL 3321 (150C°)	Green
150322	01500322HXRED	100 Pieces	18 AWG Bare Copper, UL 3321 (150C°)	Red
150322	01500322HXLBU	100 Pieces	18 AWG Bare Copper, UL 3321 (150C°)	Blue
150322	01500322HXA	100 Pieces	18 AWG Tin Plated Copper, UL 3321 (150C°)	Red
150322*	01500322HXU	100 Pieces	18 AWG Tin Plated Copper, UL 3321 (150C°)	Red

* Comes without stripped ends.
For a fuseholder customization option, please contact Littelfuse.

Disclaimer Notice - Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of and test each product selected for their own applications. Littelfuse products are not designed for, and may not be used in, all applications. Read complete Disclaimer Notice at: www.littelfuse.com/disclaimer-electronics.